
BRIGHTECH


The Jaxon Floor Lamp

with pleated shade


SHADE ASSEMBLY

1:







2:



3:




4:



1. Roll out the fabric shade wrap with the clips facing upwards, and line it up with the two wire rings, as pictured.
2. Roll the rings onto the shade wrap by snapping the clips on the wrap onto the wire rings. Take care to keep both sides aligned so that the wrap goes on straight.
3. Once fully wrapped, close the shade by attaching the two magnetic strips.
4. Gently slide the pleated shade cover over the shade to complete.

LAMP ASSEMBLY

1. Attach the socket piece (E) to the metal board (D) with hex nuts (H) and allen wrench (I) provided.
2. Assemble the lamp leg that has the cord running through it, by screwing together the lower, middle, and upper tubes (C, B, & A), gently making sure to pull the excess wire through the bottom of the lower leg while connecting the pieces so that it does not get caught on the threading (this step will be easiest to do while the lamp is lying on a flat surface).
3. Assemble the freestanding legs by screwing together the remaining poles C, B, and A.
4. Attach the two assembled free standing legs to the metal board. Once screwed in, the legs should intersect in a clockwise spiral, and the lamp frame should stand straight.
5. Unscrew the socket ring (G) from the socket, and slide the shade onto the socket with the spoked portion on the bottom as pictured. Then tighten it onto the lamp by placing the socket ring back onto the lamp and screwing that back on over the shade until it is secured and tight.
6. Screw the light bulb into the socket.
7. Plug the cord into a 110v outlet. Review reverse side of this page for important warnings and safety information prior to use.



OPERATION & USE

POWER : To turn the lamp On or Off, simply rotate the rotatry switch located on the socket of the lamp.

CUSTOMIZING THE BULB : This lamp's controls out of the box are on/off and the 9.5-watt bulb that emits a warm white light at 3000 Kelvin, which is ideal for a host of lighting environments. If desired, this bulb may be swapped out for a different bulb, including a dimming and/or color-changing smart bulb to increase customizability. Bulb specifications should not exceed the maximums represented in the Specifications on the reverse side of this page.

USING WITH A WALL SWITCH : To use this lamp with a wall switch, simply plug it into an outlet that is built to be powered with the wall switch, and turn the lamp On via the rotary switch. The lamp will then be able to be turned on and off via the light switch.

SAFETY & WARNINGS

This product uses a polarized plug so one prong is larger than the other. When plugging into an outlet, take care to plug the correct direction to avoid electric shock.

This product is intended for 110v voltage only. Use with a higher voltage is likely to cause damage to the product as well as the electrical component it is being powered by.

Do not bring this product or any of its components in contact with any water or extreme heat.

Keep between 23 degrees F & 104 degrees F, and below a humidity of 95%.

Do not use this product outside of its intended and advertised use. Do not tamper with internal parts or wiring.

Brightech is not responsible for any failures associated with modifications to this product or any of its electrical components, or when the product is used with externally purchased parts not manufactured to come with this product.

FURTHER RESOURCES | Diagnosis

Though all of our products pass rigorous pre-production quality control, we understand that sometimes things can happen. If your product is experiencing any abnormalities, please see below fo some more insight as to what may be happening & if there's anything you can do to troubleshoot. If the purchase is covered under warranty, notify us of any weaknesses or malfunctions as soon as they are discovered.
Note: Never make any temporary or permanent alterations to any parts or components of this product.

Physical or Cosmetic Damage: If the damaged portions of the product are among the separate pieces listed on the opposite side of this guide (see: Assembly), these pieces might be able to be replaced. However any parts that are connected to other parts by wiring are considered one full piece as a unit.

Light not Working: If the bulb is not working, the metal tab in the socket might have pushed in too much during production. Try unplugging the lamp and pulling out the tab slightly, to help create a connection between the two. If this doesn't fix the problem, we recommend trying to swap with another bulb. If the new bulb doesn't fix the issue, the lamp might be defective.

SPECIFICATIONS

Wattage of Bulb | 9.5 watts
Color Temperature | 3000 kelvin
Brightness | 800 lumens
Bulb Sizing | E16 Base / A19 Shape
Maximum Wattage of Socket | 100 watts

Need More Help?

Find us on the web
www.brightech.com

Connect with us
@wearebrightech

For questions or support
www.brightech.com/contact